



Dc Gear Motor

LS-20GA130



Electrical Specification

Model	Voltage	No Load		At Maximum Efficiency				Starting			
	Normal	Speed	Current	Speed	Current	Torque		Output	Torque		Current
		r/min	mA	r/min	mA	mN.m	g·cm	w	mN.m	g·cm	mA
LS-20GA130-10	12	1300	100	1000	350	14.7	150	1.5	78.4	800	1500
LS-20GA130-25	6	270	140	200	450	34.3	350	0.75	147	1500	1300
LS-20GA130-62	12	140	60	100	200	39.2	400	0.41	245	2500	500
LS-20GA130-25	12	750	130	550	1200	98	400	0.5	441	1200	4000

**Note: It's only typical technical data for reference, Motor's voltage, speed, torque, shaft dimension can be customized!*

Number Of Stages	3	4	5	6	7
Gear Ratio I	10	25	50	100	250
	12.5	31.25	62.5	125	312.5
			78.1	156.25	390.6
				195.3	488.3
Length Of Gearbox L (mm)	16	16	17.5	19	20.5

Mechanical Dimensions

